

DMX Control 192

This powerful little controller enables you to control most of Robe lighting products. The DMX Control 192 offers 192 DMX control channels; up to 12 projectors can be controlled; manual control of all projectors by joystick; fade-in time and step time adjustable via 2 faders.



Technische Spezifikation

Elektrische Spezifikationen

- Wiring options: 115, 200-230 V AC, 50/60 Hz

Mechanische Spezifikationen

- Height: 70 mm (2.7")
- Width: 176 mm (6.9")
- Length: 483 mm (19.01")
- Weight: 3.5 kg (7.7 lbs)

Steuerung und Programmierung

- Number of control channels: 192
- Up to 12 projectors each of max. 16 channels can be individually controlled
- 40 freely-programmable programs with up to 99 steps each
- 500 recordable scenes
- Manual control of all projectors by joystick
- Fade time and step time adjustable via 2 faders
- Audio, Manual and Auto trigger
- Memory card 1 Mb
- 2 parallel 3 pin XLR outputs for simple connection
- sound input: ¼" mono jack

Rigging

- 19" 4U rack mountable